PC to Video Display Pin-Outs.

1 2 3	VGA (Ana RGB) R - out G - out B - out	NEC (Dig RGBI) Intensity R G	EGA (Dig RGBI) Ground R' R	CGA (Dig RGBI) Ground Ground R	MDA (Hercules) Ground Ground N.C.
4	mon ID bit 2	В	G	G	N.C.
5	Ground	Ground	В	В	N.C.
6	R - return	Ground	G'	Intensity	Intensity
7	G - return	h-sync (+)	В'	N.C.(vid)	Video
8	B - return	v-sync (-)	h-sync (+)	h-sync (+)	h-sync (+)
9	no pin		v-sync (-)	v-sync (-)	v-sync (-)
10	sync return				
11	mon ID bit 0				
12	mon ID bit 1				
13	h-sync				
14	v-sync				
15	reserved				

NOTES

Vid on Phono

9 PIN LAYOUT	15 PIN LAYOUT
1 2 3 4 5	11 12 13 14 -
6789	6 7 8 - 10
	1 2 3 4 5

The information contained upon this page is supplied in good faith, and to the best of my knowledge is accurate. However, I accept no responsibility for damage or injury, however caused, due to the use of this data. It was originally posted to the Packet radio System by John G8MNY in JAN 2001